



## Gira G1 PoE



Specification	Order No.	Packing unit	PS	EAN
 Black glass	2069 05	1	36	4010337014270
 Glass white	2069 12	1	36	4010337014300

The Gira G1 is a multi-functional room operating device for visualising and operating a variety of building functions. For use in the KNX system and Gira door communication system.

### Features

- Operation is via a gesture-capable multi-touch display.
- Connection and communication are via LAN or WLAN depending on the version.
- Integrated loudspeaker.
- Integrated microphone with echo compensation.

#### Properties as a KNX room operating device

- Intuitive user interface that can be adapted by the end user.
- Switching, dimming, blind and shutter control, value transmitter, scene auxiliary unit.
- Status display, display of date and time, display of indoor and outdoor temperature.
- Up to 125 functions (five function folders or rooms with up to 25 functions each).
- Up to 125 seven-day time clocks with 10 switching times each.

#### Properties as a KNX room temperature controller auxiliary unit

- Use as room temperature controller auxiliary unit in combination with KNX 3 Plus push button sensor for room temperature measurement and control.
- Operating mode changeover: comfort, standby, night, and frost or heat protection.
- Operating modes can be adapted individually.
- Comfort extension using the presence button.
- A heating clock as seven-day time clock with 28 switching times.

#### Properties as home station video

- Camera changeover: specific selection of connected colour cameras.

- Control of the door opener.
- Switching the ringing tone on and off.
- Ringtone can be selected from a choice of 10 melodies.
- Call acceptance.
- Volume setting of ringing tone and voice volume.

#### Integration of Internet services

- Gira weather service: Display of the weather forecast for up to five cities.
- Gira G1 with flush-mounted connection module PoE LAN. Power is supplied via the network cable (Power over Ethernet).
- Data communication via LAN.

---

#### Technical data

##### Power consumption

- Maximum: 7 W
- Typical: 4 W
- Minimum: 2 W

##### Display

- Type: TFT
- Size: 15.3 cm (6")
- Colours: 16.7 M
- Resolution: 480 x 800 px (WVGA), 155 ppi
- Brightness: 350 cd/m<sup>2</sup>
- Contrast ratio: 1:500
- Viewing angle: > 80° all around

##### Proximity sensor

- Range: max. 50 cm
- Range of detection: 30° horizontal, 30° vertical

##### KNX standards

- DPTs value transmitter: 5.010, 6.010, 5.001, 5.004, 9.001

##### Protection type:

IP21

##### Ambient temperature:

0 °C to +45 °C

##### Power supply

- PoE performance class 0: DC 48 V PoE

##### LAN standard:

IEEE 802.3af

##### Connection cable

- Ethernet specifications: Cat.5e, Cat.6, Cat.6a, Cat.7

---

#### Notes

- Suitable for indoor use only.
- Recommended installation height: 150 cm from the floor.
- 
- Communication with the KNX installation is exclusively via the KNXnet/IP standard.
- A KNX IP router must be used to connect the Gira G1 PoE to the KNX installation. Several Gira G1 units can be operated on one KNX IP router.
- In order to ensure reliable communication via WLAN, a Gira KNX IP router (firmware version 3 and later) is required to connect the Gira G1 230 V or G1 24 V to the KNX installation. For this purpose the Gira KNX IP router (firmware version 3 and later) is specially equipped with the additional function "Reliable data communication". Several Gira G1 units can be operated on one Gira KNX IP router (firmware version 3

and later).

- Commissioning in the KNX system from ETS 4.2 or higher.
- Can be used as a home station in connection with the DCS-IP-gateway.
- When planning the system, please observe the technical information on network planning in the device documentation.
- 
- We recommend using an electronics box to install the flush-mounted connection module PoE.
- A commercially available PoE-capable switch or router or a PoE injector is required.

---

## Scope of supply

- Display module, holding frame, flush-mounted connection module PoE LAN
-